

**Specify Part
Number**
LBB 4106/00D

The Extension Power Supply unit is used in combination with a CCU to supply power to a maximum of 180 additional units. The unit can be installed at any convenient point in the system cabling due to its built-in trunk-line splitter. It is connected using loop-through cabling. The unit switches on automatically when the CCU is switched on. All outputs are protected against short circuit. It can be used freestanding on a table-top or mounted in a 19 in. rack.


Extension Power Supply Features

- Powers up to 180 additional contribution units (with PCF of 1)
- Remote mains on/off
- Easy connection to DCN

Specifications

Mounting	Free standing on a table-top or mounted in a 19" rack unit (requires 2U, fl width).
Dimensions (H x W x D)	3.93 x 8.66 x 12.12 in. (100 x 220 x 308 mm), depth including handles 13.70 in. (348 mm).
Weight	18.26 lbs. (8.3 kg)
Color	Cabinet - light gray, Handles - dark gray
Power consumption factor (PCF)	1

Listen Technologies Corporation

8535 South 700 West, Suite A
Sandy, UT 84070-2515 U.S.A.
Phone: 1.801.233.8992 or 1.800.330.0891
Fax: 1.801.233.8995
Email: info@ListenTech.com

Don't miss a single sound.

